

Tutorial pentru conectarea sistemelor cu Windows 11, versiunea 22H2 la reteaua wireless Eduroam

1. Deschideti Registry Editor cu drepturi de Administrator

In meniul Start scrieti regedit, apoi Run as Administrator.



2. Navigati la HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\services\ RasMan\PPP\EAP\13

3. Click dreapta pe fisierul 13 -> New -> DWORD



Str Gh. Baritiu, nr 26, sala 29,Cluj Napoca, 400027, Romania Telefon: +40 264 401247 / Fax: +40 264 594684 mail: admin@net.utcluj.ro www.cc.utcluj.ro

File Edit	View Favorites Help	2						
Computer\	HKEY_LOCAL_MACHINE\S	SYSTEM\CurrentControlSe	t\Services\RasMan\PPP	\EAP\13			 	
	> 🚞 QWAVEdrv	Name	Туре	Data				
	> 🚞 Ramdisk	(Default)	REG_SZ	Microsoft				
	> RasAcd	and ConfigCLSID	REG_SZ	{58AB2366-D	0597-11d1-B90E-00C04FC9B263}			
	> RasAgileVpn > RasAuto BasIOm		REG_EXPAND_SZ	%SystemRoo	t%\System32\rastls.dll			
			REG_EXPAND_SZ	@%SystemRo	oot%\system32\rastIs.dll,-2001			
	> Rasizip	ab IdentityPath	REG_EXPAND_SZ	%SystemRoo	t%\System32\rastls.dll			
		ab InteractiveUIPath	REG_EXPAND_SZ	%SystemRoo	t%\System32\rastls.dll			
	Parameters	InvokePassword	REG_DWORD	0x00000000	(0)			
	V 🚞 PPP	🐹 InvokeUsername.	REG_DWORD	0x00000000	(0)			
	> 📒 ControlPi	LANProfileTempl	REG_SZ	xml versio</td <td>n="1.0" encoding="UTF-8"?><lanpro< td=""><td></td><td></td><td></td></lanpro<></td>	n="1.0" encoding="UTF-8"?> <lanpro< td=""><td></td><td></td><td></td></lanpro<>			
	V 🚞 EAP	MPPEEncryption.	ion REG_DWORD 0x0000001 (1)					
	- = 13	MoPootPovocati,	REG_DWORD	0x0000001	(1)			
		xpand	REG EXPAND S7	%SvstemRoo	+%\System32\rastIs.dll			
	N	lew >	Key)			
	Seci Fi	ind	String Value		21444015)			
	RecPor)elete	Binary Value)			
	RasSsti D)			
	Addata Addata		QWORD (52-51) Value QWORD (64-bit) Value Multi-String Value Expandable String Value		132)			
					="1.0"?><WLANProfile xmlns="http:/</td> <td></td> <td></td>			
	> 🧮 RDPUDD							
	> 🧮 RdpVideoMinir							
	> 🚞 rdyboost							

4. Creati o noua intrare cu numele TIsVersion

1 - • • •			-	· ·
> 🚞 ControlPi		LANProfileTempl	REG_SZ	xml version="1.0" encoding="UTF-8"? <lanpro< td=""></lanpro<>
🗸 🚞 EAP		BMPPEEncryption	REG_DWORD	0x00000001 (1)
🚞 13		🕫 NoRootRevocati	REG_DWORD	0x0000001 (1)
> 🚞 25		赴 Path	REG_EXPAND_SZ	%SystemRoot%\System32\rastIs.dll
		201 PerPolicyConfig	REG_DWORD	0x0000001 (1)
Security		200 Properties	REG_DWORD	0x1328d8af (321444015)
ThirdParty		201 RolesSupported	REG_DWORD	0x0000003 (3)
RasPppoe	- 1	35 StandaloneSupp	REG_DWORD	0x0000000 (0)
rdbss		11 TIsVersion	REG_DWORD	0x00000fc0 (4032)
RDMANDK		WLANProfileTem	REG_SZ	xml version="1.0"? <WLANProfile xmlns="http:/</td>
rdpbus				
RDPDR				

5. Click dreapta pe TlsVersion -> Modify si scrieti valoarea fc0 -> OK

	Ā	CENTRUL DE CC Str Gh. Baritiu, n Telefon: +4	DMUNICATII "PUSZTAI KALMAN" r 26, sala 29,Ciuj Napoca, 400027, Romania o 264 401247 / Fax: +40 264 594684 mail: admin@net.utcluj.ro www.cc.utcluj.ro
DIN CLOS-INAL OCA			
Edit DWORD (32-bit) Value		×	
Value name:			
TIsVersion			
Value data:	Base		
fc0	 Hexadecimal 		
	ODecimal		
	ОК	Cancel	

6. Dupa restart la calculator, ar trebui sa va puteti conecta la reteaua Eduroam